



# Radio Čerenkov measurements in salt

## UH Salt Detector Testbed

P. Miočinović

*University of Hawaii at Manoa, Honolulu, Hawaii, USA*

ARENA Workshop, DESY Zeuthen

May 19, 2005



# Outline



- Motivation
- Experimental setup
- Analysis progress
- Summary and Outlook



# Motivation


- Detecting **the first** coherent radio Čerenkov signal **of natural origin**
- Exploration of **Askaryan effect** in rock salt in **broad range of energies**
- Evaluating potential of rock salt as a medium for detection of UHE particles
- Electronics evaluation testbed for ANITA and SalSA



# Experiment



- **Target material: 20 tons of synthetic rock salt**
  - rock salt blocks, weighing 22.7 kg each
  - purity of the salt: 93-96%
- **Bowtie antennas** embedded in salt and amplified by cable TV technology
- Computer controlled waveform readout
- Camac-based **trigger** from **MACRO** particle counters; 100 GeV threshold,  $\sim 2500$  ev/day






# Experimental Setup



- 20,000 kg of synthetic rock-salt placed in the rectangular wooden box.
  - index of refraction  $n = 2.4$ ;  $\theta_c = 65^\circ$
  - specific density  $\rho = 2.08 \text{ g/cm}^3$
  - radiation length  $X_0 = 13.5 \text{ cm}$
  - critical energy  $E_c = 52.6 \text{ MeV}$
- dimensions of the box 12 x 1.2 x 0.8 m
- interior walls covered with thin zinc plated steel sheets
- two rows of antennas were placed on the lowest layer of salt blocks.
- 3 MACRO counters track charged particles as a trigger for antenna readout.








# Antennas and RF readout



- Dual linear polarized bowtie antenna printed on PCB
- Frequency response  $\sim 0.2-2.0$  GHz





- RF readout through a **custom, low-power digitizer chip** (STRAW2) mounted on cPCI card (ANITA/SalSA prototype)
- 12 RF channels per card
- sampling rate **2.12 GS/sec**,  $\sim 250$  samples per waveform





# Data Taking



- For each trigger, 48 RF signal and 12 PMT signal channels are readout
- Two dimensional reconstruction of particle track is based on PMT timing
- 2.7 sec later, background RF reading is taken



fully captured **particle transit window** (~ 60 ns)



# MC expectations



- based on Askaryan signal strength measured at SLAC,  $1\sigma$  voltage level for cascade energy of **2.8 TeV**
- Total expected event rate is **3.45 events/yr**
- $2\sigma$  rate 0.86 ev/yr





# Analysis




## RF data filtering:

- need to **digitally filter out RFI**; 50-95 MHz and 200-260 MHz bands due to local FM (college radio station next door) and UHF TV stations

## Strategy I:

- build **matched filter** based on SLAC measurements of bowtie response to Askaryan pulse + lab measured system response
- **scan** all events **for coincident pulses** consistent with the expected shape
- analyzed 2 months of data, but **no clear candidates** yet




Bowtie response to Askaryan pulse



# Analysis, cont.

## Strategy II:

- To improve our sensitivity, coherently add RF data; i.e. add sub-threshold events in order to boost SNR
- Look for a **statistical increase** in RF power seen by antennas during triggered events compared to background RF events
- So far, analyzed 1 month of data and we have no statistically meaningful result, yet. Better event selection required.





# Summary

- The testbed experiment is looking for **Askaryan radio pulses** induced by **cosmic ray secondaries**
- Built on a shoestring budget (\$40-50k), but proving to be **essential for hardware development platform** for both ANITA and SaISA
- Motivated by a good physics goal, not just a technology testbed



# Outlook



- Data rates are limited by:
  - **RF noise**
    - custom low noise amplifiers
    - better RF readout with new digitizing chips and cards
    - place experiment further away from RF noise pollution
  - **Atmospheric depth**
    - move to higher ground for increased particle flux
  - **Size, size, and size**
    - Increase the volume of instrumented salt